

Reason 1.0 MIDI Controller Chart - Page 1

| MIDI Contr. # | MIDI Controller Name | Mixer 14:2 | NN-19 | Subtractor | Redrum | Dr. Rex | CF-1010 Chorus | DDL-1 Delay |
|---------------|---|-----------------------------|-------------------------------|------------------------------|-----------------------|-------------------------------|-------------------|-----------------|
| 0 | ControlBankSelect | | | | | | | |
| 1 | ControlModulationWheel | | Mod Wheel | Mod Wheel | | Mod Wheel | | |
| 2 | ControlBreathController | | | | | | | |
| 3 | ControlUndefined3 | | | | Pattern Select | | | |
| 4 | ControlFootController | | | | | | | |
| 5 | ControlPortamentoTime | | Portamento | Portamento | Flam Amount | | | |
| 6 | ControlDataEntryMSB | | | | | | | |
| 7 | ControlChannelVolume | Master Level | Master Level | Master Level | Master Level | Master Level | | |
| 8 | ControlBalance | Channel 1 Level | | | Drum 1 Level | | | |
| 9 | ControlUndefined9 | Channel 2 Level | Amp Env Decay | Amp Env Decay | Drum 2 Level | Amp Env Decay | Enabled | Enabled |
| 10 | ControlPan | Channel 3 Level | | | Drum 3 Level | | | Pan |
| 11 | ControlExpressionController | | | | | | | |
| 12 | ControlEffectControl1 | Channel 4 Level | Amp Env Sustain | Amp Env Sustain | Drum 4 Level | Amp Env Sustain | Delay | DelayTime16th |
| 13 | ControlEffectControl2 | Channel 5 Level | | | Drum 5 Level | | Feedback | Feedback |
| 14 | ControlUndefined14 | Channel 6 Level | Filter Env Attack | Filter Env Attack | Drum 6 Level | Filter Env Attack | Rate | Dry Wet Balance |
| 15 | ControlUndefined15 | Channel 7 Level | Filter Env Decay | Filter Env Decay | Drum 7 Level | Filter Env Decay | Modulation Amount | TimeBase |
| 16 | ControlGeneralPurpose1 | Channel 8 Level | Filter Env Sustain | Filter Env Sustain | Drum 8 Level | Filter Env Sustain | | Step Length |
| 17 | ControlGeneralPurpose2 | Channel 9 Level | Filter Env Release | Filter Env Release | Drum 9 Level | Filter Env Release | | |
| 18 | ControlGeneralPurpose3 | Channel 10 Level | Filter Env Amount | Filter Env Amount | Drum 10 Level | Filter Env Amount | | |
| 19 | ControlGeneralPurpose4 | Channel 11 Level | Filter Env Invert | Filter Env Invert | Drum 1 Pan | | | |
| 20 | ControlUndefined20 | Channel 12 Level | Sample Start | Osc1Wave | Drum 2 Pan | | | |
| 21 | ControlUndefined21 | Channel 13 Level | Osc Octave | Osc1 Octave | Drum 3 Pan | Osc Octave | | |
| 22 | ControlUndefined22 | Channel 14 Level | Osc Semitone | Osc1 Semitone | Drum 4 Pan | Transpose Loop | | |
| 23 | ControlUndefined23 | Channel 1 Pan | Osc Fine Tune | Osc1 Fine Tune | Drum 5 Pan | Osc Fine Tune | | |
| 24 | ControlUndefined24 | Channel 2 Pan | Osc Env Amount | | Drum 6 Pan | Osc Env Amount | | |
| 25 | ControlUndefined25 | Channel 3 Pan | Osc | Osc1 Kbd Track | Drum 7 Pan | | | |
| 26 | ControlUndefined26 | Channel 4 Pan | LFO 1 Rate | LFO1 Rate | Drum 8 Pan | LFO1 Rate | | |
| 27 | ControlUndefined27 | Channel 5 Pan | LFO 1 Level | LFO1 Amount | Drum 9 Pan | LFO1 Amount | | |
| 28 | ControlUndefined28 | Channel 6 Pan | LFO 1 Wave | LFO1 Wave | Drum 10 Pan | LFO1 Wave | | |
| 29 | ControlUndefined29 | Channel 7 Pan | LFO 1 Dest | LFO1 Dest | Drum 1 Send 1 Amount | LFO1 Dest | | |
| 30 | ControlUndefined30 | Channel 8 Pan | | | Drum 2 Send 1 Amount | | | |
| 31 | ControlUndefined31 | Channel 9 Pan | | | Drum 3 Send 1 Amount | | | |
| 32 | ControlLSB0 (Bank select) | | | | | | | |
| 33 | ControlLSB1 (ModWheel) | Channel 10 Pan | Filter Freq Mod Wheel Amount | Filter Freq Mod Wheel Amount | Drum 4 Send 1 Amount | Filter Freq Mod Wheel Amount | | |
| 34 | ControlLSB2 (Breath) | Channel 11 Pan | Filter Res Mod Wheel Amount | Filter Res Mod Wheel Amount | Drum 5 Send 1 Amount | FilterRes Mod Wheel Amount | | |
| 35 | ControlLSB3 (Undefined) | Channel 12 Pan | Filter Decay Mod Wheel Amount | LFO1Mod Wheel Amount | Drum 6 Send 1 Amount | Filter Decay Mod Wheel Amount | | |
| 36 | ControlLSB4 (Foot controller) | Channel 13 Pan | Amp Mod Wheel Amount | FM Mod Wheel Amount | Drum 7 Send 1 Amount | AmpVel | | |
| 37 | ControlLSB5 (Portamento time) | Channel 14 Pan | LFO1 Mod Wheel Amount | Phase Diff Mod Wheel Amount | Drum 8 Send 1 Amount | | | |
| 38 | ControlLSB6 (DataEntry LSB) | | | | | | | |
| 39 | ControlLSB7 (Channel Volume) | Channel 1 Aux Send 1 Level | Pitch Bend Range | Pitch Bend Range | Drum 9 Send 1 Amount | Pitch Bend Range | | |
| 40 | ControlLSB8 (Balance) | Channel 2 Aux Send 1 Level | Filter Freq Ext Mod | Filter Freq Ext Mod | Drum 10 Send 1 Amount | | | |
| 41 | ControlLSB9 (Undefined) | Channel 3 Aux Send 1 Level | LFO1 Ext Mod | LFO1 Ext Mod | Drum 1 Send 2 Amount | | | |
| 42 | ControlLSB10 (Pan) | Channel 4 Aux Send 1 Level | Amp Ext Mod | Amp Ext Mod | Drum 2 Send 2 Amount | | | |
| 43 | ControlLSB11 (Expression) | Channel 5 Aux Send 1 Level | Ext Mod Select | Ext Mod Select | Drum 3 Send 2 Amount | | | |
| 44 | ControlLSB12 (Effect control 1) | Channel 6 Aux Send 1 Level | FM Ext Mod | FM Ext Mod | Drum 4 Send 2 Amount | | | |
| 45 | ControlLSB13 (Effect control 2) | Channel 7 Aux Send 1 Level | Amp Vel Amount | Amp Env Vel Amount | Drum 5 Send 2 Amount | | | |
| 46 | ControlLSB14 (Undefined) | Channel 8 Aux Send 1 Level | Filter Env Vel Amount | Filter Env Vel | Drum 6 Send 2 Amount | Filter Env Vel Amount | | |
| 47 | ControlLSB15 (Undefined) | Channel 9 Aux Send 1 Level | Filter Decay Vel Amount | Filter Decay Vel Amount | Drum 7 Send 2 Amount | Filter Decay Vel Amount | | |
| 48 | ControlLSB16 (General purpose 1) | Channel 10 Aux Send 1 Level | Amp Attack Vel Amount | Amp Attack Vel Attack | Drum 8 Send 2 Amount | | | |
| 49 | ControlLSB17 (General purpose 2) | Channel 11 Aux Send 1 Level | Sample Start Vel Amount | FM Vel Amount | Drum 9 Send 2 Amount | | | |
| 50 | ControlLSB18 (General purpose 3) | Channel 12 Aux Send 1 Level | | Mod Env Vel Amount | Drum 10 Send 2 Amount | | | |
| 51 | ControlLSB19 (General purpose 4) | Channel 13 Aux Send 1 Level | | Phase Vel Amount | Drum 1 Pitch1 | | | |
| 52 | ControlLSB20 (Undefined) | Channel 14 Aux Send 1 Level | | Filter Freq2 Vel Amount | Drum 2 Pitch2 | | | |
| 53 | ControlLSB21 (Undefined) | Channel 1 Aux Send 2 Level | | Mix Vel Amount | Drum 3 Pitch3 | | | |
| 54 | ControlLSB22 (Undefined) | Channel 2 Aux Send 2 Level | | | Drum 4 Pitch4 | | | |
| 55 | ControlLSB23 (Undefined) | Channel 3 Aux Send 2 Level | Solo Sample | | Drum 5 Pitch5 | | | |
| 56 | ControlLSB24 (Undefined) | Channel 4 Aux Send 2 Level | Spread Mode | | Drum 6 Pitch6 | | | |
| 57 | ControlLSB25 (Undefined) | Channel 5 Aux Send 2 Level | Stereo Spread | | Drum 7 Pitch7 | | | |
| 58 | ControlLSB26 (Undefined) | Channel 6 Aux Send 2 Level | | | Drum 8 Pitch8 | | | |
| 59 | ControlLSB27 (Undefined) | Channel 7 Aux Send 2 Level | | | Drum 9 Pitch9 | | | |
| 60 | ControlLSB28 (Undefined) | Channel 8 Aux Send 2 Level | | | Drum 10 Pitch10 | | | |
| 61 | ControlLSB29 (Undefined) | Channel 9 Aux Send 2 Level | | | Drum 1 Tone | | | |
| 62 | ControlLSB30 (Undefined) | Channel 10 Aux Send 2 Level | | | Drum 2 Tone | | | |
| 63 | ControlLSB31 (Undefined) | Channel 11 Aux Send 2 Level | | | Drum 10 Tone | | | |
| 64 | ControlDamperPedal (Sustain) | | | | | | | |
| 65 | ControlPortamentoOnOff | Channel 12 Aux Send 2 Level | | | Drum 6 Pitch | | | |
| 66 | ControlSostenuto | Channel 13 Aux Send 2 Level | | | Drum 7 Pitch | | | |
| 67 | | Channel 14 Aux Send 2 Level | | | Drum 1 Vel to Level | | | |
| 68 | ControlLegatoFootSwitch | Channel 1 Bass Amount | Key Mode | Key Mode | Drum 2 Vel to Level | | | |
| 69 | ControlHold2 | Channel 2 Bass Amount | | | Drum 3 Vel to Level | | | |
| 70 | ControlSoundController1 (Sound Variation) | Channel 3 Bass Amount | | | Drum 4 Vel to Level | | | |

Reason 1.0 MIDI Controller Chart - Page 2

| MIDI Contr. # | MIDI Controller Name | Mixer 14:2 | NN-19 | Subtractor | Redrum | Dr. Rex | CF-1010 Chorus | DDL-1 Delay |
|---------------|--|--------------------------|------------------|---------------------|-----------------------------|-----------------|----------------|-------------|
| 71 | ControlSoundController2 (Harmonic Intensity) | Channel 4 Bass Amount | Filter Q | Filter Resonance | Drum 5 Vel to Level | Filter Q | | |
| 72 | ControlSoundController3 (Release time) | Channel 5 Bass Amount | Amp Env Release | Amp Env Release | Drum 6 Vel to Level | Amp Env Release | | |
| 73 | ControlSoundController4 (Attack time) | Channel 6 Bass Amount | Amp Env Attack | Amp Env Attack | Drum 7 Vel to Level | Amp Env Attack | | |
| 74 | ControlSoundController5 (Brightness) | Channel 7 Bass Amount | Filter Freq | Filter Freq | Drum 8 Vel to Level | Filter Freq | | |
| 75 | ControlSoundController6 | Channel 8 Bass Amount | Filter On/Off | Filter2 On | Drum 9 Vel to Level | Filter On | | |
| 76 | ControlSoundController7 | Channel 9 Bass Amount | Filter Type | Filter Type | Drum 10 Vel to Level | Filter Type | | |
| 77 | ControlSoundController8 | Channel 10 Bass Amount | Filter Kbd Track | Filter Kbd Track | Drum 1 Decay | | | |
| 78 | ControlSoundController9 | Channel 11 Bass Amount | | Filter2 Resonance | Drum 2 Decay | | | |
| 79 | ControlSoundController10 | Channel 12 Bass Amount | | Filter2 Freq | Drum 3 Decay | | | |
| 80 | ControlGeneralPurposeController5 | Channel 13 Bass Amount | | Filter Link Freq On | Drum 4 Decay | | | |
| 81 | ControlGeneralPurposeController6 | Channel 14 Bass Amount | | Noise On | Drum 5 Decay | | | |
| 82 | ControlGeneralPurposeController7 | Channel 1 Treble Amount | | Noise Level | Drum 6 Decay | | | |
| 83 | ControlGeneralPurposeController8 | Channel 2 Treble Amount | | Noise Decay | Drum 7 Decay | | | |
| 84 | ControlPortamentoControl | Channel 3 Treble Amount | | Noise Color | Drum 8 Decay | | | |
| 85 | ControlUndefined85 | Channel 4 Treble Amount | | Mod Env Gain | Drum 9 Decay | | | |
| 86 | ControlUndefined86 | Channel 5 Treble Amount | | Mod Env Invert | Drum 10 Decay | | | |
| 87 | ControlUndefined87 | Channel 6 Treble Amount | | Mod Env Attack | Drum 3 SampleStart | | | |
| 88 | ControlUndefined88 | Channel 7 Treble Amount | | Mod Env Decay | Drum 4 SampleStart | | | |
| 89 | ControlUndefined89 | Channel 8 Treble Amount | | Mod Env Sustain | Drum 5 SampleStart | | | |
| 90 | ControlUndefined90 | Channel 9 Treble Amount | | Mod Env Release | Drum 8 SampleStart | | | |
| 91 | ControlEffects1Depth | Channel 10 Treble Amount | | Mod Env Dest | Drum 9 SampleStart | | | |
| 92 | ControlEffects2Depth | Channel 11 Treble Amount | | Osc1 PhaseMode | Pattern Enabled | | | |
| 93 | ControlEffects3Depth | Channel 12 Treble Amount | | Osc1 Phase Diff | | | | |
| 94 | ControlEffects4Depth | Channel 13 Treble Amount | | Osc2 On | Drum 6 Vel to Pitch Bend | | | |
| 95 | ControlEffects5Depth | Channel 14 Treble Amount | | Osc2 Wave | Drum 7 Vel to Pitch Bend | | | |
| 96 | ControlDataIncrement | | | | | | | |
| 97 | ControlDataDecrement | | | | | | | |
| 98 | ControlNonRegisteredParameterNumberLSB | | | | | | | |
| 99 | ControlNonRegisteredParameterNumberMSB | | | | | | | |
| 100 | ControlRegisteredParameterNumberLSB | | | | | | | |
| 101 | ControlRegisteredParameterNumberMSB | | | | | | | |
| 102 | ControlUndefined102 | Line 1 Send Aux3 Level | | Osc2 Octave | Drum 6 Pitch Bend Rate Rate | | | |
| 103 | ControlUndefined103 | Line 2 Send Aux3 Level | | Osc2 Semitone | Drum 7 Pitch Bend Rate Rate | | | |
| 104 | ControlUndefined104 | Line 3 Send Aux3 Level | | Osc2 Fine Tune | Drum 1 Vel ToTone | | | |
| 105 | ControlUndefined105 | Line 4 Send Aux3 Level | | Osc2 Mode | Drum 2 Vel ToTone | | | |
| 106 | ControlUndefined106 | Line 5 Send Aux3 Level | | Osc2 Phase Diff | Drum 10 Vel ToTone | | | |
| 107 | ControlUndefined107 | Line 6 Send Aux3 Level | | Osc Mix | Drum 3 Vel to Sample Start | | | |
| 108 | ControlUndefined108 | Line 7 Send Aux3 Level | | FM Amount | Drum 4 Vel to Sample Start | | | |
| 109 | ControlUndefined109 | Line 8 Send Aux3 Level | | Ring Mod | Drum 5 Vel to Sample Start | | | |
| 110 | ControlUndefined110 | Line 9 Send Aux3 Level | | LFO2 Rate | Drum 8 Vel to Sample Start | | | |
| 111 | ControlUndefined111 | Line 10 Send Aux3 Level | | LFO2 Amount | Drum 9 Vel to Sample Start | | | |
| 112 | ControlUndefined112 | Line 11 Send Aux3 Level | | LFO2 Delay | | | | |
| 113 | ControlUndefined113 | Line 12 Send Aux3 Level | | LFO2 Dest | | | | |
| 114 | ControlUndefined114 | Line 13 Send Aux3 Level | | LFO2 Kbd Track | | | | |
| 115 | ControlUndefined115 | Line 14 Send Aux3 Level | | Osc2 Kbd Track | | | | |
| 116 | ControlUndefined116 | Aux 1 Return Level | | | | | | |
| 117 | ControlUndefined117 | Aux 2 Return Level | | | | | | |
| 118 | ControlUndefined118 | Aux 3 Return Level | | | | | | |
| 119 | ControlUndefined119 | Aux 4 Return Level | | | | | | |
| 120 | ControlReservedForChannelModeMessages120 | | | | | | | |
| 121 | ControlReservedForChannelModeMessages121 | | | | | | | |
| 122 | ControlReservedForChannelModeMessages122 | | | | | | | |
| 123 | ControlReservedForChannelModeMessages123 | | | | | | | |
| 124 | ControlReservedForChannelModeMessages124 | | | | | | | |
| 125 | ControlReservedForChannelModeMessages125 | | | | | | | |
| 126 | ControlReservedForChannelModeMessages126 | | | | | | | |
| 127 | ControlReservedForChannelModeMessages127 | | | | | | | |
| 128 | | | | | | | | |
| 129 | | | | | | | | |
| 130 | | | | | | | | |
| 131 | | | | | | | | |
| 132 | | | | | | | | |
| 133 | | | | | | | | |
| 134 | | | | | | | | |
| 135 | | | | | | | | |
| 136 | | | | | | | | |
| 137 | | | | | | | | |
| 138 | | | | | | | | |
| 139 | | | | | | | | |
| 140 | | | | | | | | |
| 141 | | | | | | | | |

Reason 1.0 MIDI Controller Chart - Page 3

| MIDI Contr. # | MIDI Controller Name | COMP-01 Compressor | D-11 Distortion | ECF-42 Filter | PEQ2 Param. EQ | PH-90 Phaser | Reverb | ReBirth Input | Matrix |
|---------------|---|--------------------|-----------------|---------------|------------------|----------------------|-----------|---------------|----------------|
| 0 | ControlBankSelect | | | | | | | | |
| 1 | ControlModulationWheel | | | | | | | | |
| 2 | ControlBreathController | | | | | | | | |
| 3 | ControlUndefined3 | | | | | | Algorithm | | Pattern Select |
| 4 | ControlFootController | | | | | | | | |
| 5 | ControlPortamentoTime | | | | | | | | |
| 6 | ControlDataEntryMSB | | | | | | | | |
| 7 | ControlChannelVolume | | | | | | | | |
| 8 | ControlBalance | | | | | | | | |
| 9 | ControlUndefined9 | Enabled | Enabled | Enabled | Enabled | Enabled | Enabled | Enabled | |
| 10 | ControlPan | | | | | | | | |
| 11 | ControlExpressionController | | | | | | | | |
| 12 | ControlEffectControl1 | Threshold | Amount | Mode | Filter A Gain | Split | Size | | |
| 13 | ControlEffectControl2 | Attack | Foldback | Sustain | Filter B Gain | Feedback | Damping | | |
| 14 | ControlUndefined14 | Release | | Release | Filter B Enabled | Rate | Decay | | |
| 15 | ControlUndefined15 | | | Velocity | | Frequency Modulation | Dry/Wet | | |
| 16 | ControlGeneralPurpose1 | Ratio | | Env Amount | | Width | | | |
| 17 | ControlGeneralPurpose2 | | | | | | | | |
| 18 | ControlGeneralPurpose3 | | | | | | | | |
| 19 | ControlGeneralPurpose4 | | | | | | | | |
| 20 | ControlUndefined20 | | | | | | | | |
| 21 | ControlUndefined21 | | | | | | | | |
| 22 | ControlUndefined22 | | | | | | | | |
| 23 | ControlUndefined23 | | | | | | | | |
| 24 | ControlUndefined24 | | | | | | | | |
| 25 | ControlUndefined25 | | | | | | | | |
| 26 | ControlUndefined26 | | | | | | | | |
| 27 | ControlUndefined27 | | | | | | | | |
| 28 | ControlUndefined28 | | | | | | | | |
| 29 | ControlUndefined29 | | | | | | | | |
| 30 | ControlUndefined30 | | | | | | | | |
| 31 | ControlUndefined31 | | | | | | | | |
| 32 | ControlLSB0 (Bank select) | | | | | | | | |
| 33 | ControlLSB1 (ModWheel) | | | | | | | | |
| 34 | ControlLSB2 (Breath) | | | | | | | | |
| 35 | ControlLSB3 (Undefined) | | | | | | | | |
| 36 | ControlLSB4 (Foot controller) | | | | | | | | |
| 37 | ControlLSB5 (Portamento time) | | | | | | | | |
| 38 | ControlLSB6 (DataEntry LSB) | | | | | | | | |
| 39 | ControlLSB7 (Channel Volume) | | | | | | | | |
| 40 | ControlLSB8 (Balance) | | | | | | | | |
| 41 | ControlLSB9 (Undefined) | | | | | | | | |
| 42 | ControlLSB10 (Pan) | | | | | | | | |
| 43 | ControlLSB11 (Expression) | | | | | | | | |
| 44 | ControlLSB12 (Effect control 1) | | | | | | | | |
| 45 | ControlLSB13 (Effect control 2) | | | | | | | | |
| 46 | ControlLSB14 (Undefined) | | | | | | | | |
| 47 | ControlLSB15 (Undefined) | | | | | | | | |
| 48 | ControlLSB16 (General purpose 1) | | | | | | | | |
| 49 | ControlLSB17 (General purpose 2) | | | | | | | | |
| 50 | ControlLSB18 (General purpose 3) | | | | | | | | |
| 51 | ControlLSB19 (General purpose 4) | | | | | | | | |
| 52 | ControlLSB20 (Undefined) | | | | | | | | |
| 53 | ControlLSB21 (Undefined) | | | | | | | | |
| 54 | ControlLSB22 (Undefined) | | | | | | | | |
| 55 | ControlLSB23 (Undefined) | | | | | | | | |
| 56 | ControlLSB24 (Undefined) | | | | | | | | |
| 57 | ControlLSB25 (Undefined) | | | | | | | | |
| 58 | ControlLSB26 (Undefined) | | | | | | | | |
| 59 | ControlLSB27 (Undefined) | | | | | | | | |
| 60 | ControlLSB28 (Undefined) | | | | | | | | |
| 61 | ControlLSB29 (Undefined) | | | | | | | | |
| 62 | ControlLSB30 (Undefined) | | | | | | | | |
| 63 | ControlLSB31 (Undefined) | | | | | | | | |
| 64 | ControlDamperPedal (Sustain) | | | | | | | | |
| 65 | ControlPortamentoOnOff | | | | | | | | |
| 66 | ControlSostenuto | | | | | | | | |
| 67 | | 50 | | | | | | | |
| 68 | ControlLegatoFootSwitch | | | | | | | | |
| 69 | ControlHold2 | | | | | | | | |
| 70 | ControlSoundController1 (Sound Variation) | | | | | | | | |

Reason 1.0 MIDI Key Mapping

| MIDI key | Mixer 14:2 | Redrum | Dr. REX |
|----------|---------------------|-----------------|---------------------|
| 0 | Channel 1 Mute | | Transpose -12 |
| 1 | | | Transpose -11 |
| 2 | Channel 2 Mute | | Transpose -10 |
| 3 | | | Transpose -9 |
| 4 | Channel 3 Mute | | Transpose -8 |
| 5 | Channel 4 Mute | | Transpose -7 |
| 6 | | | Transpose -6 |
| 7 | Channel 5 Mute | | Transpose -5 |
| 8 | | | Transpose -4 |
| 9 | Channel 6 Mute | | Transpose -3 |
| 10 | | | Transpose -2 |
| 11 | Channel 7 Mute | | Transpose -1 |
| 12 | Channel 8 Mute | | Transpose 0 |
| 13 | | | Transpose +1 |
| 14 | Channel 9 Mute | | Transpose +2 |
| 15 | | | Transpose +3 |
| 16 | Channel 10 Mute | | Transpose +4 |
| 17 | Channel 11 Mute | | Transpose +5 |
| 18 | | | Transpose +6 |
| 19 | Channel 12 Mute | | Transpose +7 |
| 20 | | | Transpose +8 |
| 21 | Channel 13 Mute | | Transpose +9 |
| 22 | | | Transpose +10 |
| 23 | Channel 14 Mute | | Transpose +11 |
| 24 | Channel 1 Solo | | Transpose +12 |
| 25 | | | |
| 26 | Channel 2 Solo | | Trigger entire loop |
| 27 | | | |
| 28 | Channel 3 Solo | | |
| 29 | Channel 4 Solo | | Trigger slice 1 |
| 30 | | | Trigger slice 2 |
| 31 | Channel 5 Solo | | Trigger slice 3 |
| 32 | | | Trigger slice 4 |
| 33 | Channel 6 Solo | | Trigger slice 5 |
| 34 | | | Trigger slice 6 |
| 35 | Channel 7 Solo | | Trigger slice 7 |
| 36 | Channel 8 Solo | Trigger Drum 1 | Trigger slice 8 |
| 37 | | Trigger Drum 2 | Trigger slice 9 |
| 38 | Channel 9 Solo | Trigger Drum 3 | Trigger slice 10 |
| 39 | | Trigger Drum 4 | Trigger slice 11 |
| 40 | Channel 10 Solo | Trigger Drum 5 | Trigger slice 12 |
| 41 | Channel 11 Solo | Trigger Drum 6 | Trigger slice 13 |
| 42 | | Trigger Drum 7 | Trigger slice 14 |
| 43 | Channel 12 Solo | Trigger Drum 8 | Trigger slice 15 |
| 44 | | Trigger Drum 9 | Trigger slice 16 |
| 45 | Channel 13 Solo | Trigger Drum 10 | Trigger slice 17 |
| 46 | | | Trigger slice 18 |
| 47 | Channel 14 Solo | | Trigger slice 19 |
| 48 | Channel 1 Eq On/Off | Drum 1 Mute | Trigger slice 20 |
| 49 | | | Trigger slice 21 |
| 50 | Channel 2 Eq On/Off | Drum 2 Mute | Trigger slice 22 |
| 51 | | | Trigger slice 23 |
| 52 | Channel 3 Eq On/Off | Drum 3 Mute | Trigger slice 24 |
| 53 | Channel 4 Eq On/Off | Drum 4 Mute | Trigger slice 25 |
| 54 | | | Trigger slice 26 |
| 55 | Channel 5 Eq On/Off | Drum 5 Mute | Trigger slice 27 |
| 56 | | | Trigger slice 28 |
| 57 | Channel 6 Eq On/Off | Drum 6 Mute | Trigger slice 29 |
| 58 | | | Trigger slice 30 |
| 59 | Channel 7 Eq On/Off | Drum 7 Mute | Trigger slice 31 |
| 60 | Channel 8 Eq On/Off | Drum 8 Mute | Trigger slice 32 |
| 61 | | | Trigger slice 33 |
| 62 | Channel 9 Eq On/Off | Drum 9 Mute | Trigger slice 34 |
| 63 | | | Trigger slice 35 |

| MIDI key | Mixer 14:2 | Redrum | Dr. REX |
|----------|----------------------|-----------------|------------------|
| 64 | Channel 10 Eq On/Off | Channel 10 Mute | Trigger slice 36 |
| 65 | Channel 11 Eq On/Off | | Trigger slice 37 |
| 66 | | | Trigger slice 38 |
| 67 | Channel 12 Eq On/Off | | Trigger slice 39 |
| 68 | | | Trigger slice 40 |
| 69 | Channel 13 Eq On/Off | | Trigger slice 41 |
| 70 | | | Trigger slice 42 |
| 71 | Channel 14 Eq On/Off | | Trigger slice 43 |
| 72 | | Channel 1 Solo | Trigger slice 44 |
| 73 | | | Trigger slice 45 |
| 74 | | Channel 2 Solo | Trigger slice 46 |
| 75 | | | Trigger slice 47 |
| 76 | | Channel 3 Solo | Trigger slice 48 |
| 77 | | Channel 4 Solo | Trigger slice 49 |
| 78 | | | Trigger slice 50 |
| 79 | | Channel 5 Solo | Trigger slice 51 |
| 80 | | | Trigger slice 52 |
| 81 | | Channel 6 Solo | Trigger slice 53 |
| 82 | | | Trigger slice 54 |
| 83 | | Channel 7 Solo | Trigger slice 55 |
| 84 | | Channel 8 Solo | Trigger slice 56 |
| 85 | | | Trigger slice 57 |
| 86 | | Channel 9 Solo | Trigger slice 58 |
| 87 | | | Trigger slice 59 |
| 88 | | Channel 10 Solo | Trigger slice 60 |
| 89 | | | Trigger slice 61 |
| 90 | | | Trigger slice 62 |
| 91 | | | Trigger slice 63 |
| 92 | | | Trigger slice 64 |
| 93 | | | Trigger slice 65 |
| 94 | | | Trigger slice 66 |
| 95 | | | Trigger slice 67 |
| 96 | | | Trigger slice 68 |
| 97 | | | Trigger slice 69 |
| 98 | | | Trigger slice 70 |
| 99 | | | Trigger slice 71 |
| 100 | | | Trigger slice 72 |
| 101 | | | Trigger slice 73 |
| 102 | | | Trigger slice 74 |
| 103 | | | Trigger slice 75 |
| 104 | | | Trigger slice 76 |
| 105 | | | Trigger slice 77 |
| 106 | | | Trigger slice 78 |
| 107 | | | Trigger slice 79 |
| 108 | | | Trigger slice 80 |
| 109 | | | Trigger slice 81 |
| 110 | | | Trigger slice 82 |
| 111 | | | Trigger slice 83 |
| 112 | | | Trigger slice 84 |
| 113 | | | Trigger slice 85 |
| 114 | | | Trigger slice 86 |
| 115 | | | Trigger slice 87 |
| 116 | | | Trigger slice 88 |
| 117 | | | Trigger slice 89 |
| 118 | | | Trigger slice 90 |
| 119 | | | Trigger slice 91 |
| 120 | | | Trigger slice 92 |
| 121 | | | Trigger slice 93 |
| 122 | | | Trigger slice 94 |
| 123 | | | Trigger slice 95 |
| 124 | | | Trigger slice 96 |
| 125 | | | Trigger slice 97 |
| 126 | | | Trigger slice 98 |
| 127 | | | Trigger slice 99 |