

Control transmitter frequency range	Protected TV station location
470-476 MHz	Jacksonville, IL 39°45'52" 90°30'29". Mt. Pleasant, MI 43°34'24" 84°46'21". Oxford, OH 39°30'26" 84°44'09". Washington, DC 38°57'17" 77°00'17".
476-482 MHz	Champaign, IL 40°04'11" 87°54'45". Madison, WI 43°03'01" 89°29'15". Parkersburg, WV 39°20'50" 81°33'56". Fort Wayne, IN 41°05'35" 85°10'42". Lancaster, PA 40°15'45" 76°27'49". South Bend, IN 41°36'26" 86°27'48". Philadelphia, PA 40°02'30" 75°14'24".
482-488 MHz	None.
488-494 MHz	Johnstown, PA 40°19'47" 78°53'45".
494-500 MHz	Washington, DC 38°57'49" 77°06'18".
500-506 MHz	Waterbury, CT 41°31'02" 73°01'00".
506-512 MHz	

* * * * *

\$22.651 [Corrected]

On page 59546, in the first column, in \$22.651, the table should read as follows:

Houston			
488.0125	491.0125	488.0875	491.0875
488.0375	491.0375	488.1125	491.1125
488.0625	491.0625	488.1375	491.1375
New York-Northern New Jersey			
473.0125	479.0125	473.1625	479.1625
473.0375	479.0375	473.1875	479.1875
473.0625	479.0625	473.2125	479.2125
473.0875	479.0875	473.2375	479.2375
473.1125	479.1125	473.2625	479.2625
473.1375	479.1375	473.2875	479.2875

* * * * *

\$22.725 [Corrected]

On page 59551, in the third column, in \$22.725, on page 59551 the table should read as follows:

Central office	Rural subscriber	Central office	Rural subscriber
VHF Channels			
152.03	158.49	152.57	157.83
152.06	158.52	152.60	157.86
152.09	158.55	152.63	157.89
152.12	158.58	152.66	157.92
152.15	158.61	152.69	157.95
152.18	158.64	152.72	157.98
152.21	158.67	152.75	158.01
152.51	157.77	152.78	158.04
152.54	157.80	152.81	158.07

UHF Channels			
454.025	459.025	454.350	459.350
454.050	459.050	454.375	459.375
454.075	459.075	454.400	459.400
454.100	459.100	454.425	459.425
454.125	459.125	454.450	459.450
454.150	459.150	454.475	459.475
454.175	459.175	454.500	459.500
454.200	459.200	454.525	459.525
454.225	459.225	454.550	459.550
454.250	459.250	454.575	459.575
454.275	459.275	454.600	459.600
454.300	459.300	454.625	459.625
454.325	459.325	454.650	459.650

* * * * *

\$22.757 [Corrected]

On page 59553, in the first column, in \$22.757, the table should read as follows:

UHF CHANNELS—SHARED WITH PRIVATE RADIO SERVICES			
Rural subscriber	Central office	Rural subscriber	Central office
816.2375	861.2375	816.1125	861.1125
817.2375	862.2375	817.1125	862.1125
818.2375	863.2375	818.1125	863.1125
819.2375	864.2375	819.1125	864.1125
820.2375	865.2375	820.1125	865.1125
816.2125	861.2125	816.0875	861.0875
817.2125	862.2125	817.0875	862.0875
818.2125	863.2125	818.0875	863.0875
819.2125	864.2125	819.0875	864.0875
820.2125	865.2125	820.0875	865.0875
816.1875	861.1875	816.0625	861.0625
817.1875	862.1875	817.0625	862.0625
818.1875	863.1875	818.0625	863.0625
819.1875	864.1875	819.0625	864.0625
820.1875	865.1875	820.0625	865.0625
816.1625	861.1625	816.0375	861.0375
817.1625	862.1625	817.0375	862.0375
818.1625	863.1625	818.0375	863.0375
819.1625	864.1625	819.0375	864.0375
820.1625	865.1625	820.0375	865.0375
816.1375	861.1375	816.0125	861.0125
817.1375	862.1375	817.0125	862.0125
818.1375	863.1375	818.0125	863.0125
819.1375	864.1375	819.0125	864.0125
820.1375	865.1375	820.0125	865.0125

* * * * *

\$22.905 [Corrected]

On page 59561, in the first column, in \$22.905, the table should read as follows:

Base	Mobile	Base	Mobile
CHANNEL BLOCK A			
416 communication channel pairs			
869.040	824.040	890.010	845.010
869.070	824.070	890.040	845.040
879.990	834.990	891.480	846.480
21 control channel pairs			
	834.390	879.390	
	834.420	879.420	
	834.990	879.990	

CHANNEL BLOCK B			
416 communication channel pairs			
880.020	835.020	891.510	846.510
880.050	835.050	891.540	846.540
889.980	844.980	893.970	848.970
21 control channel pairs			
	835.020	880.020	
	835.050	880.050	
	835.920	880.620	

\$22.1007 [Corrected]

On page 59573, in the third column, in \$22.1007, the tables should read as follows:

Central	Subscriber	Central	Subscriber
488.025	491.025	488.225	491.225
488.050	491.050	488.250	491.250
488.075	491.075	488.275	491.275
488.100	491.100	488.300	491.300
488.125	491.125	488.325	491.325
488.150	491.150	488.350	491.350
488.175	491.175	488.375	491.375
488.200	491.200	488.400	491.400

(2) These channels may be assigned for use by offshore central (base/fix) or subscriber stations (fixed, temporary fixed, surface and/or airborne mobile) as indicated, for voice-grade general communications and private line service:

Central	Subscriber	Central	Subscriber
488.425	491.425	488.575	491.575
488.450	491.450	488.600	491.600
488.475	491.475	488.625	491.625
488.500	491.500	488.650	491.650
488.525	491.525	488.675	491.675
488.550	491.550	488.700	491.700

(3) These channels may be assigned for use by relay stations in systems where it would be impractical to provide offshore radiotelephone service without the use of relay stations.

Central	Subscriber	Central	Subscriber
488.725	491.725	488.775	491.775
488.750	491.750	488.800	491.800